Wi-Fi Quick Installation Guideline (iOS APP)

1. Download and install the "RcsCloud" APP from App Storeorscanthe QR Code as below.



- 2. Open the APP, tap the **Register** button to enter next page. According to the prompts, type in the information to create an account.
- 3. Type in the user name and password, tap the **Log in** button to enter the main interface.
- 4. Wireless Router Connection
 - 4.1 Confirm the WLAN is 2.4 G network connection by mobile phones (5G network cannot be used), and check inverter Wi-Fi AP "SUNLINE-XXXXXX" is existed". (Fig.1)
 - 4.2 Open the APP, tap the "+" button to add new device, type in the router password, tap Next

button to continue network setting. (Fig.2)

- 4.3 According to APP tips, connect to the Wi-Fi "SUNLINE-XXXXXX" of the inverter directly. (Fig.3)
- 4.4 Then return to the APP interface and follow the prompts step by step. (Fig.4)

10:32	al 🕆 🕞	10:32 .ul 중 🗆	10:32	al 🗈	10:33 III 4G
Settings WLAN		AP配网	Settings WLAN		
			WLAN		11:23 atl * ①
WLAN		WiFi Name: SLTek	SUNLINE-A_B5E47A Unsecured Network	∻ (i)	<款定 无线局域网
✓ SLTek	🕯 🗢 🚺	WiFi Password: sunline168			无线局域网
			MY NETWORKS		/ XXXXX ▲ ♥ 〔 CONG ▲ ♥ 〔
MY NETWORKS			SLTek	🔒 🤶 🚺	HWWFL628636
SLTek_5G	🔒 🗢 🚺		SLTek_5G	a 🗢 (i)	лияна 000 🔒 🐨 🕠
SUNLINE-A_B5E47A	? (j́)	Next	OTHER NETWORKS		60N6 • • 0
OTHER NETWORKS			ChinaNet-C03D4A	🔒 🗟 🚺	
ChinaNet-C03D4A	🔒 🤶 🚺		ChinaNet-C03D4A-5G	a 🤶 🚺	Config and search device, please wait.
ChinaNet-C03D4A-5G	🔒 🤶 🚺		ChinaNet-itxu	a 🤶 🚺	
ChinaNet-itxu	🔒 🤶 🚺	"sunline168"	ChinaNet-Z9iQ	a < i	
ChinaNet-Z9iQ	🔒 🗢 🚺	qwertyuiop	TP-LINK_0FA8	۵ 🗢 (أ)	
TP-LINK_0FA8	🔒 🤶 🚺		TP-LINK_wansu	a 🗢 i	
TP-LINK_wansu	🔒 🗢 🚺	asdfghjkl	总仓	a 🗟 🕽	
总仓	🔒 🗢 🚺		总仓1	۵ 🗢 🚺	
总仓1	🔒 🤶 🚺	123 😂 space return	Other		
Other		٩			Your current Wi-Fi is:SUNLINE-A_B5E47A
		¥ ¥	Apps Using WL	>	

(Fig.1)(Fig.2)(Fig.3)(Fig.4)

5. If the routing connection failure, we can reset the inverter Wi-Fi module by LCD interface and try again. Inverter Wi-Fi reset process as below.
Press "ENTER" button 3s to enter setting mode → Press "DOWN" button to find program 37 → Press "ENTER" button to enter program 37 → Press "DOWN" button to find reset option → Press "ENTER" button to confirm reset option →

Press "ESC" button to finished the setting.